


MULTIGANG SWITCH BOXES

DRAWN


2-1/8" DEEP

WITH RAISED GROUND EMBOSS & DEVICE EARS


Cat. No.	No. of Gangs	Bracket & Setback	Knockouts		Dimension W x H	Cu. Inch	Std. Pkg.
			Sides	Bottom			
DHB-2	2	-	4 - 1/2", 4 - CKO	2 - 1/2", 2 - 3/4"	4" x 4"	30.3	25
DHB-3	3	-	4 - 1/2", 6 - CKO	2 - 1/2", 2 - 3/4"	5-3/4" x 4"	44.0	25
DHB-4	4	-	4 - 1/2", 8 - CKO	5 - 1/2", 4 - 3/4"	7-1/2" x 4"	57.8	20
DHB-3-B	3	B, 9/16"	2 - 1/2", 6 - CKO	2 - 1/2", 2 - 3/4"	5-3/4" x 4"	44.0	20
DHB-4-B	4	B, 9/16"	2 - 1/2", 8 - CKO	5 - 1/2", 4 - 3/4"	7-1/2" x 4"	57.8	20
DHB-2-FB	2	FB, 9/16"	2 - 1/2", 4 - CKO	2 - 1/2", 2 - 3/4"	4" x 4"	30.3	25
DHB-3-FB	3	FB, 9/16"	2 - 1/2", 6 - CKO	2 - 1/2", 2 - 3/4"	5-3/4" x 4"	44.0	20
DHB-4-FB	4	FB, 9/16"	2 - 1/2", 8 - CKO	5 - 1/2", 4 - 3/4"	7-1/2" x 4"	57.8	20




DHB-2




DHB-3




DHB-4




DHB-3-B




DHB-4-B



DHB-2-FB



DHB-3-FB



DHB-4-FB

MULTIGANG SWITCH BOXES


WELDED

1-5/8" DEEP


& LOW VOLTAGE PARTITION

Cat. No.	No. of Gangs	Knockouts		Dimension W x H	Cu. Inch	Std. Pkg.
		Sides	Bottom			
SB-2	2	6 - 1/2", 6 - MKO	3 - 1/2", 2 - 3/4"	6-13/16" x 4-9/16"	56.3	5
SB-3	3	8 - 1/2", 6 - MKO	6 - 1/2", 4 - 3/4"	8-5/8" x 4-9/16"	65.0	5
SB-4	4	8 - 1/2", 8 - MKO	6 - 1/2", 4 - 3/4"	10-7/16" x 4-9/16"	80.0	5
SB-5	5	10 - 1/2", 8 - MKO	6 - 1/2", 4 - 3/4"	12-1/4" x 4-9/16"	94.8	5
SB-6	6	10 - 1/2", 10 - MKO	6 - 1/2", 4 - 3/4"	14-1/16" x 4-9/16"	111.1	1
SB-7	7	12 - 1/2", 10 - MKO	9 - 1/2", 6 - 3/4"	15-7/8" x 4-9/16"	127.0	1
SB-8	8	12 - 1/2", 12 - MKO	9 - 1/2", 6 - 3/4"	17-11/16" x 4-9/16"	142.1	1
SB-9	9	14 - 1/2", 12 - MKO	9 - 1/2", 6 - 3/4"	19-1/2" x 4-9/16"	157.9	1
SB-10	10	14 - 1/2", 14 - MKO	9 - 1/2", 6 - 3/4"	21-3/8" x 4-9/16"	172.1	1
SB-D	Partition for 1-5/8" SB Boxes, flat or raised cover					25


- ▶ **600V** MKO's and CKO's suitable for bonding without any additional bonding means up to 600V
- ▶ Acceptable for use in 2-hour rated walls (2-Gang only)
- ▶ Visit www.ul.com or QCIT Guide on page W1 for more information



SB-2




SB-3



SB-6



SB-D



Mount Multigang boxes between studs on Orbit's SSB System. See pg. P1 for more info

