


## NL-418 / NL-419

### Adjustable Eyeball with Baffle

#### TRIM DIMENSIONS



Trim OD: 5"  
Height: 3"

#### FEATURES

##### Trim

Metal trim with adjustable eyeball can be rotated 358° horizontally and 35° vertically. Precision spun 0.040 aluminum baffle with deep grooves to reduce aperture glare. Gimbal ring allows lamp to be mounted on top of the trim. Separate trim ring available in metal, may also be used with custom combination of plastic or metal ring finishes.

##### Mounting

Trim includes three trim clips that securely mount trim in housing.

##### Compatible Housings

Compatible with Line Voltage and Low Voltage housings.  
See individual specification sheets for more information.

##### Lamp

###### Line Voltage

50W 120V MR16 GU10 Max. (NSL-401AT/10; NSLIC-401AT/10; NSLR-404AT/10)

###### Low Voltage

20W-75W 12V MR16 (NL-401 Series; NL-402 Series; NLIC-401 Series; NLIC-402 Series; NLR-403 Series; NLR-404 Series; NLR-405 Series)

##### Labels and Listings

cULus Listed for Damp Location when used with compatible housing.

#### Adjustable Eyeball with Baffle

- NL-418BB: Black Adjustable Eyeball with Black Baffle and Black Metal Ring
- NL-418CO: Copper Adjustable Eyeball with Copper Baffle and Copper Metal Ring
- NL-418N: Natural Metal Adjustable Eyeball with Natural Metal Baffle and Natural Metal Ring
- NL-418WB: White Adjustable Eyeball with Black Baffle and White Metal Ring
- NL-418WW: White Adjustable Eyeball with White Baffle and White Metal Ring
- NL-419C: Chrome Adjustable Eyeball with Black Baffle and Chrome Metal Ring
- NL-419G: Gold Adjustable Eyeball with Black Baffle and Gold Metal Ring

# NORALIGHTING.

Type

Project

Catalog No.

Lamp/Wattage

#### Compatible Housings

##### LINE VOLTAGE

Item Number	Installation Type	Lamp	Dimensions
NSL-401AT/10	Non-IC Air-Tight New Const.	50W MR16	W: 5-5/8" L: 8-1/2" H: 5-3/4"
NSLIC-401AT/10	IC Air-Tight New Construction	50W MR16	W: 8" L: 12-5/8" H: 8"
NSLR-404AT/10	Non-IC Air-Tight Remodel	50W MR16	W: 4-1/4" L: 11-1/4" H: 5-5/8"

##### LOW VOLTAGE

NL-401QAT/20	Non-IC AT New Const., Mag.	20W MR16	W: 6" L: 9" H: 5-1/2"
NL-401QAT/37	Non-IC AT New Const., Mag.	37W MR16	W: 6" L: 9" H: 5-1/2"
NL-401QAT	Non-IC AT New Const., Mag.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401/50/277AT	Non-IC AT New Const., Mag.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401AT/1EL	Non-IC AT New Const., Elec.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401AT/2EL	Non-IC AT New Const., Elec.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401/75	Non-IC AT New Const., Mag.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/277	Non-IC AT New Const., Mag.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/1EL	Non-IC AT New Const., Elec.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/2EL	Non-IC AT New Const., Elec.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-402S/20	Non-IC Shallow New Con., Mag.	20W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S/37	Non-IC Shallow New Con., Mag.	37W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S	Non-IC Shallow New Con., Mag.	50W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S/1EL	Non-IC Shallow New Con., Elec.	50W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NLIC-401QSAT/20	IC Air-Tight New Const., Mag.	20W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401QSAT/37	IC Air-Tight New Const., Mag.	37W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401QSAT	IC Air-Tight New Const., Mag.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401AT/277V	IC Air-Tight New Const., Mag.	50W MR16	W: 10-3/4" L: 17-3/4" H: 7-1/2"
NLIC-401AT/1EL	IC Air-Tight New Const., Elec.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401AT/2EL	IC Air-Tight New Const., Elec.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-402QSAT/20	IC Air-Tight Shallow NC, Mag.	20W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402QSAT/37	IC Air-Tight Shallow NC, Mag.	37W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402QSAT	IC Air-Tight Shallow NC, Mag.	50W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402AT/1EL	IC Air-Tight Shallow NC, Elec.	50W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLR-403S/20	Non-IC Shallow Remodel, Mag.	20W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S/37	Non-IC Shallow Remodel, Mag.	37W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S	Non-IC Shallow Remodel, Mag.	50W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S/1EL	Non-IC Shallow Remodel, Elec.	50W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-404QAT/20	Non-IC Air-Tight Remodel, Mag.	20W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404QAT/37	Non-IC Air-Tight Remodel, Mag.	37W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404QAT	Non-IC Air-Tight Remodel, Mag.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404/50/277	Non-IC Air-Tight Remodel, Mag.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404AT/1EL	Non-IC Air-Tight Remodel, Elec.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404AT/2EL	Non-IC Air-Tight Remodel, Elec.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404/75	Non-IC Remodel, Magnetic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/277	Non-IC Remodel, Magnetic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/1EL	Non-IC Remodel, Electronic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/2EL	Non-IC Remodel, Electronic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-405AT/20	Non-IC Air-Tight Remodel	20W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"
NLR-405AT/37	Non-IC Air-Tight Remodel	37W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"
NLR-405AT	Non-IC Air-Tight Remodel	50W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"

# NORALIGHTING.

6505 Gayhart St., Commerce, CA 90040  
www.noralighting.com • Specifications subject to change without notice. © 2011  
Phone: 800.686.6672 • FAX: 800.500.9955 • e-mail: nora@noralighting.com