

BRAVO FROST TW

120V Tunable White LED Linear

Nora Lighting's low-profile LED Bravo FROST Tunable White fixtures provide excellent and even illumination on all surfaces. At only 10 watts per foot, Bravo FROST TW produces 850 lumens at a crisp sharp 90+ CRI. Each luminaire contains it's own driver allowing for 120V feed and longer single runs than low voltage systems. It is one of the most powerful linear and energy efficient system on the market.

FEATURES

- Architectural extruded aluminum construction
- Symmetrical internal reflectors produce broad even light
- Frosted lens eliminates LED diode image
- 120V linear system
- 850 lumens / 10 Watts per foot
- Field Selectable CCT (3000K, 3500K or 4000K @ 90+ CRI)
- Available in 4 different lengths: 12", 16", 24" or 32"
- Linkable up to 270 Watts fixtures (about 30')
- Less than 1" in depth.
- Self contained dimmable electronic driver in each unit
- 0° to 90° adjustable mounting brackets included
- 5-Year Limited Warranty
- ENERGY STAR® Certified
- Can be used to comply with 2019 Title 24 – part 6 High Efficacy LED light source requirements
- cULus Listed for Dry Location



BRAVO FROST TUNABLE WHITE 120V TUNABLE WHITE LED LINEAR FIXTURE

LENGTH / WATTAGE	COLOR TEMPERATURE	FINISH
NUDTW-9812 12" / 10W	(blank) Field Selectable CCT (3000K, 3500K or 4000K)	/W White
NUDTW-9816 16" / 13W		
NUDTW-9824 24" / 20W		
NUDTW-9832 32" / 26W		


Example: **NUDTW-9812/W** - 12" 850lm / 10W Bravo FROST Tunable White, White finish

Tunable White

Selectable CCT
3000K, 3500K, 4000K



90° Adjustability
with included
mounting brackets



3-wire system
meets most code
requirements





Hardwire Junction Box

NUA-902W
Junction box used to power NUDTW-98 Series using jumper cable or NUA-904W (3-Wire Hardwire Connector)
Width: 3-5/8" Length: 6-1/4" Height: 1"



72" 3-Wire Hardwire Connector

NUA-904W
3-Wire connector used to hardwire fixture to NUA-902W (Junction Box).



72" Cord and Plug

NUA-905W
6' Grounded AC power cord to connect fixture to an outlet.



End-to-End Connector

NUA-903W
Used to join two fixtures together or to NUA-902W (Junction Box) seamlessly. One included with each luminaire.



Jumper Cables

NUA-906W	6"
NUA-912W	12"
NUA-924W	24"
NUA-972W	72"

Used to join two fixtures together or to NUA-902W (Junction Box).



Adjustable Mounting Brackets

NUA-609W
Set of Two
Mounting brackets used to mount fixture to surface. Adjust from 0° to 90°. Two brackets are included with each luminaire.