

# J2 Track

**Description:** Two circuit track with independently controllable circuits  
**Power per Circuit:** 1920 W max  
**Operating Current:** Each circuit is rated 20A (2 x 20A = 40A max)

- Saves on installation costs by eliminating the need for long separate feed runs



## Track Sections

Model	Length	Finish	Description
<b>J2</b> J2 Track	<b>T4</b> 4'	<b>BK</b> Black <b>WT</b> White	120V 3-wire, wide style track
	<b>T8</b> 8'		
	<b>T12</b> 12'		

Example: **J2-T4-WT**


Each section includes two matching end caps.

## J Clip


Model	Description
2-Circuit Track Conversion Clip	Each 4' section includes 3 Each 8' section includes 6 Each 12' section includes 9



**JCLIP**



Locks connectors on luminaire into 2-circuit mode



## Quick Connect Adapter

Model	Finish
Quick Connect Adapter	<b>BK</b> Black <b>WT</b> White



**EN-JQ50AR**

Min. Load: 1W  
Max Load: 50W

## Track Suspension

Model	Length	Finish
All Track Suspension Kit	<b>SK</b> 18 18" 36 36" 24 24" 48 48"	<b>BK</b> Black <b>WT</b> White
Suspension Kit Extender	<b>R</b> 18 18" 24 24" 36 36" 48 48" 72 72"	<b>BK</b> Black <b>WT</b> White
Sloped Ceiling Adapter	<b>SK14</b>	<b>BK</b> Black <b>WT</b> White
Rod Coupler	<b>RI</b>	<b>BK</b> Black <b>WT</b> White
Suspension Adjustment Collar Kit	<b>SK05</b> Includes two collars	<b>BK</b> Black <b>WT</b> White
Low Voltage Track Head Extension	<b>X</b> 6 6" 12 12" 18 18" 24 24" 36 36" 48 48"	<b>BK</b> Black <b>WT</b> White
Wall Mount Suspension Bracket	<b>TBKT</b> 18"	<b>BK</b> Black <b>WT</b> White
Wire Way Cover	<b>J2-WCOV</b>	<b>BK</b> Black <b>WT</b> White

## Accessories

Model	Finish	Dimensions
Live End Connector	<b>J2-LE</b> <b>BK</b> Black <b>WT</b> White	4 3/4"
Live End BX Connector	<b>J2-BXLE</b> <b>BK</b> Black <b>WT</b> White	5 7/8"
1" Power Connector	<b>J2-IPWR</b> <b>BK</b> Black <b>WT</b> White	7"
1" Connector - Left	<b>J2-LLEFT</b> <b>BK</b> Black <b>WT</b> White	4 1/4" x 4 1/4"
1" Connector - Right	<b>J2-LRIGHT</b>	
T Connector	<b>J2-T</b> <b>BK</b> Black <b>WT</b> White	7" x 4 1/4"
X Connector	<b>J2-X</b> <b>BK</b> Black <b>WT</b> White	7" x 7"
I Connector	<b>J2-I</b> <b>BK</b> Black <b>WT</b> White	4 1/2"
I Dead End Connector	<b>J2-IDEC</b> <b>BK</b> Black <b>WT</b> White	3 1/2"
Flexible Track Connector	<b>J2-FLX</b> <b>BK</b> Black <b>WT</b> White	11 1/2"
T-Bar Drop Ceiling Attachment	<b>T-BARCLIP</b>	1 1/2" x 1 1/4"
Octagon Box Cover	<b>J2-UCP</b> <b>BK</b> Black <b>WT</b> White	4 1/8" x 4 1/8"
T-Bar End Feed	<b>J2-TBLE</b> <b>BK</b> Black <b>WT</b> White	4 1/8" x 4 1/8"

Example: **J2-FLX-BK**