



### EK119 / EK119B Emergency-Call (Call for Assistance) Kit(s)



NOTE: Image shown is with Pull Cord Station Activated

#### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The Emergency (Call for Assistance) kit(s) shall be Alpha Communications® **EK119** (without buzzer) or **EK119B** (with buzzer/horn) or approved equal. Dome lights shall include a translucent plastic cover mounted on a flame retardant ABS plastic panel, and shall mount over a conventional 1 or 2-gang electrical back box. Dome lights shall feature Hi-Brightness LEDs to eliminate costly bulb replacement, and minimize downtime.

The Emergency Call switch (**SF119/2A**) shall be mounted on a durable ABS plastic faceplate marked "EMERGENCY". Signaling for assistance shall only require a short pull in any direction on the 6' nylon cord. Canceling the call shall be possible only at the point of origin. Unit shall mount on single-gang electric "gem" box or plaster ring., and shall feature a RED 'call placed' Indicator when activated. The **SF119/2A** switch shall also have a 2nd set of low-voltage contacts for a 2nd device activation as needed.

The built-in buzzer/horn (in the **EK119B** kits) shall sound as long as the dome light is lighted (activated).

Contractor shall observe all local and national electrical and building codes.

#### EK119 / EK119B EMERGENCY-CALL KITS

The Alpha Communications® **EK119** and **EK119B** Emergency-Call Kits are the ideal solution for a stand-alone 'Call for Assistance' applications where an emergency switch is required. Typically these kits are ideal for use in health care facilities, public rest-rooms (toilets) and handicapped areas. These new and improved kits now feature Dome Lights with Hi-Brightness White LEDs so there is no need for costly bulb replacements!

##### The model **EK119** consists of:

- 1- **SF119/2A** Emergency Pull Cord station (RED Indicator style)
- 1- **SS106** 24VAC (U.L Listed) pigtail Transformer
- 1 - **CDL101LED** Corridor Dome Light (LED type - without a buzzer).

##### The model **EK119B** consists of

- 1- **SF119/2A** Emergency Pull Cord station (RED Indicator style)
- 1- **SS106** 24VAC (U.L Listed) pigtail Transformer
- 1 - **CDL123B** Corridor Dome Light (LED type - with a built-in buzzer/horn).

#### FEATURES

- Ideal for 'Toilet Alarm' or other Stand-Alone application
- Hi-Brightness White LEDs - No Bulb Replacement!!
- Safe - Low Voltage Wiring

#### DOME LIGHT SPECIFICATIONS

<b>Dimensions:</b>	Height: 5.20" (133mm) Width: 4.55" (116mm) Projects: 3.50" (89mm) from mounting surface
<b>AC Current:</b>	<b>EK119:</b> 24VAC, 10mA <b>EK119B:</b> 24VAC, 170mA
<b>Mounting:</b>	Fits standard 1 or 2-gang box. Minimum depth of box to be no less than 1.75".
<b>Finish:</b>	Translucent white plastic cover mounted on a flame retardant, fog white ABS plastic panel.

#### PULL CORD SPECIFICATIONS

<b>Dimensions:</b>	Height: 4.50" (114mm) (less cord) Width: 2.75" (70mm) Depth: 1.50" (38mm) (into wall)
<b>Faceplate:</b>	White ABS (flame retardant) plastic.
<b>Connection:</b>	Pigtail wire leads (2 separate sets of 2 leads)

	<b>Mounting:</b>	Standard single-gang electrical box
	<b>Marking:</b>	"EMERGENCY" in Black Letters
	<b>Call Notification:</b> <b>Placed</b>	Sliding Red Window Type

**Alpha Communications**  
42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599  
TOLL-FREE: (800) 666-4800 • Web: [www.alphacommunications.com](http://www.alphacommunications.com) • Email: [info@alphacommunications.com](mailto:info@alphacommunications.com)

Copyright© 1998-2023 Alpha Communications® - All Rights Reserved.  
Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.