



SKU: B07Y926SS8

Retrofit Alarm Kit



Connect your existing hardwired contact sensors to your wireless Ring Alarm system, and control it all from the Ring app. Get started with help from a professional alarm installer (recommended but not required). Wire up to 8 zones with one Retrofit Alarm Kit (Note: not for use with wired smoke or CO detectors or existing keypads).

TECH SPECS

Dimensions: 4.53 in. X 4.53 in. X 1.0 in. (11.51 cm. X 11.51 cm. X 2.54 cm.)

Available colors: White

FEATURES

Connect up to 8 wired contact sensor zones and allow them to communicate wirelessly to the Ring Alarm Base Station.

POWER AND CONNECTIVITY

Power: 2 X 3V Lithium 123 Batteries Included, non-rechargeable

Battery Life: 5 years with 100 events per day. "Events" defined as either open/close events or the 70 minute supervisory message sent from the device to the Base Station to report that the device is online.

Connectivity: Z-Wave (250-foot range to Base Station)

INSTALLATION

Mounts to Walls, Double-sided Tape Provided, Screw Mounting Optional (screws are not provided)

Operating Conditions: 32°F to 120°F (0°C to 49°C)

Setup Requirements: Ring Alarm Security Kit (sold separately)